Automatically start OMNI Select after power outage

November 12, 2014

Purpose and overview

These instructions explain how to configure your computer so that OMNI Select can automatically start and collect data after a power outage. For this to happen, two things must happen

For OMNI Select to automatically start after a power outage, two things need to happen.

1. The computer must automatically power on.
2. Windows must automatically log on.

Configure your computer to automatically start after a power outage

To configure your computer to automatically start after a power outage, you need to make changes in the BIOS.

1. Restart your computer and then press DELETE repeatedly immediately after it powers on. This should take you to the BIOS.
   NOTE: Some models of computers use F2, F10, or F12 instead.
2. Look for a **Power** or **Advanced** menu/page for a power failure setting. It might be called **Restore on AC/Power Loss**, **AC Power Recovery**, **After Power Failure**, or something similar.
3. Change the setting to **ON.**
4. Save the changes and then exit the BIOS.

Configure Windows to automatically log on

These instructions are for Windows Vista, 7, and 8. Windows XP is not supported.

1. Click **Start** or press ⊞ + R.
2. Type `netplwiz` and then press ENTER.
   The User Accounts window displays.
3. On the **Users** tab, deselect/remove the checkmark next to *Users must enter a user name and password to use this computer*.
4. Click **OK**.
   The Automatically Log on window displays.
5. Type the user name and password you want to use to automatically log on to Windows and then click **OK**.
6. Restart the computer and make sure Windows automatically logs on.

If you have any problems or questions, please contact Phason using the contact information below.

Phason Inc.
2 Terracon Place
Winnipeg, Manitoba, Canada
R2J 4G7

Phone: 204-233-1400
Fax: 204-233-3252
E-mail: support@phason.ca
Web site: www.phason.ca