APP-010: Supra clock bug

Problem

There is a bug in the Supra that affects the clock of controls using a growth curve. Problems do not happen immediately, but *will* occur the first time the power has been cycled off and then on.

If your control uses a growth curve but has not experienced any problems, it is important that you follow the steps in the solution to prevent any future problems.

If you are unsure if your control uses a growth curve, you can check by following these steps.

1. From the Main Menu, press **Settings** (1) and then **Growth Curve** (4).
2. For each zone you are controlling, check if the status is **Enabled** or **Disabled**. Enabled means the control was using a growth curve.

Solution

1. From the Main Menu, press **Maintenance** (2) and then **Set Clock** (3).
2. Adjust the clock using the numbers on the arrows on the keypad. When finished, move the cursor to **Save Changes** and then press **ENTER**.
3. Go back to the Set Clock screen and confirm that it is correct.
4. From the Main Menu, press **Settings** (1) and then **Growth Curve** (4).
5. For each zone controlled by a growth curve, adjust the **Current Day** to the correct day. *Use the numbers on the keypad, not the + /– .*
6. Press BACK to exit the Growth Curve display.
7. Returned to the Growth Curve display and verify the changes are correct.
8. Switch off the power to the control for at least 10 seconds and then switch it on again.
9. Check the clock and the growth curve values to make sure they are still correct.

 ©Phason Inc.